

## 1. Product Feature

This light is color changer, adopt high bright LED as light source and excellent metal alloy as shell. With the advantage of very bright, long life, save energy, rich color, light, convenient to stall, and available environment compare to traditional lights.

## 2. Product uses environment and notes items

It must be operated in dry and indoor environment, temperature -20 degree to +50 degree. Pls keep it far from rain water and darkish place. Don't watch the light by your eyes directly for a long time.

## 3. Install

This light can be installed in any angle. After installation, pls check if the screws are fixed tightly. light. (Figure Appendix 1)

## 4. Operation

This light has 4 kinds of control models: 1, DMX512 control 2, automatic operation 3, sound action 4, Master/slave

### 4.1 DMX512 operation:

When the dip switch "10" is on and "1,2,3,4,5,6,7,8,9" is off, the light accept DMX512 signal. It works as DMX512 model. You can dip "1,2,3,4,5,6,7,8,9" to set the DMX address

### 4.2 Automatic operation

The function list is:

ON	OFF	Function
----	-----	----------

5	1,2,3,4,6,7,8,9,10	Red
6	1,2,3,4,5,7,8,9,10	Green
7	1,2,3,4,5,6,8,9,10	Blue
8	1,2,3,4,5,6,7,9,10	White
9	1,2,3,4,5,6,7,8,10	Sound action
1,9	2,3,4,5,6,7,8,10	Sound action 1
2,9	1,3,4,5,6,7,8,10	Sound action 2
1,2,9	3,4,5,6,7,8,10	Sound action 3
3,9	1,2,4,5,6,7,8,10	Sound action 4
1,3,9	2,4,5,6,7,8,10	Sound action 5
2,3,9	1,4,5,6,7,8,10	Sound action 6
1,2,3,9	4,5,6,7,8,10	Sound action 7
4,9	1,3,5,6,7,8,10	Sound action 8
1,4,9	2,3,5,6,7,8,10	Sound action 9
2,4,9	1,3,5,6,7,8,10	Sound action 10
1,2,4,9	3,5,6,7,8,10	Sound action 11
3,4,9	1,2,5,6,7,8,10	Sound action 12
1,3,4,9	2,5,6,7,8,10	Sound action 13
8,9	1,2,3,4,5,6,7,10	Automatic operation 1 (you can dip 1-5 to adjust the s
7,8,9	1,2,3,4,5,6,10	Automatic operation 2 (you can dip 1-5 to adjust the s
6,7,9	1,2,3,4,5,8,10	Automatic operation 3 (you can dip 1-5 to adjust the s
7,9	1,2,3,4,5,6,8,10	Automatic operation 4 (you can dip 1-5 to adjust the s
6,8,9	1,2,3,4,5,7,10	Automatic operation 5 (you can dip 1-5 to adjust the s
6,7,8,9	1,2,3,4,5,10	Automatic operation 6 (you can dip 1-5 to a
10	1,2,3,4,5,6,7,8,9	Slave mode

# USER MANUAL

## HIGH POWER RGBW STROBE

### 4.3 DMX channel list:

Channels	Function
Channel1:	Dimmer
Channel2:	Strobe
0-4	No function
5-63	strobe action from slow to fast
64-68	Sound action strobe
69-128	Thunder strobe
129-132	Sond action Thunder strobe
133-192	Gradually brightness from slow to fast
193-196	Sound action gradually brightness
197-245	Gradually dim from slow to fast
246-250	Sound action gradually dim
251-255	No function
Channel3:	Red
Channel4:	Green
Channel5:	Blue
Channel6:	White
Channel7:	Marco
0-9	No function
10-169	fixed colors
170-179	Automatical operation1;
180-189	Automatical operation2
190-199	Automatical operation3
200-209	Automatical operation4;
210-219	Automatical operation5
220-255	Automatical operation6
CH8:	Marco speed

### Technical standard

8DMX512 channel

Working model:DMX512,automatical operation, sound action, master/slave;

Adop super bright 1W LED lamp; Beam angel:45°

Source:R:3 pcs\*1W;G:3pcs\*1W;B:3pcs\*1W;W:3pcs\*1W

Color temperature:less than 6000K

Voltage:AC90V-240V/50 or 60Hz Power:30W

Pls read this user manual before you operate it